

## **GEKO 9001 E-S/SEBA**

**Order number** : **V5048**

El. capacity 1 ~ : **9,2 kVA = 7,36kW** Steady state  
Power factor :  $\cos \varphi = 0,8$   
Voltage 1~ : 230V  
Max. sum. current 1 ~ : 40 A  
Current1~(CEE) : 40 A  
Current1~(Schuko) : 16 A  
Max. starting current  
Cos  $\varphi$  0,6 1 ~ : 60 A  
Frequency : 50 Hz  
Noise pressure (10m Distance) : **70 dB(A)**  
Length x Width x Height : 790mm x 550mm x 650mm  
Weight : 138 kg

### **Engine**

Producer : Briggs & Stratton  
Type : 380447 (Petrol)  
Operating mode : 4-Stroke, 3000 <sup>1/min</sup> / 1800 <sup>1/min</sup>  
Number of cylinders : 2  
Fuel consumption by  
25% / 50% / 75% / 100% load : 2,54l/h / 3,36l/h / 4,46l/h / 5,52l/h  
Cooling system : Air  
Engine power : 12,1 kW  
Start system : Electro start

### **Generator**

Type : Synchronous  
Cooling System : Air  
Safety class : IP 54

### **Filling quantity**

Engine oil : 1,7 Litre  
Fuel tank : 10 Litre

### **Control panel and connections**

- 1 x Recoil hand starter
- 2 x Plug socket 1~ 230V/16A (Schuko)
- 1 x Plug socket 1~ 230V/63A (CEE)
- 1 x Operating time counter

